


Industrial Type
TYPE 807
(U.X. BASE)
OUTPUT BEAM
TETRODE



The BRIMAR type 807 is an indirectly heated beam tetrode for use in the output stages of large audio equipment. The valve is fitted with a low-loss base and may be used as R.F. amplifier or frequency multiplier in transmitters. Above 60 Mc/s the ratings must be reduced and at 120 Mc/s the ratings must not exceed 50 per cent. of the maximum.

RATINGS

Heater Voltage	6.3 volts
Heater Current	0.9 amp.
Anode Voltage	600 volts
Anode Dissipation	25 watts
Screen (g ₂) Voltage	300 volts
Screen Dissipation	3.5 watts

} Absolute
Maximum

OPERATING CHARACTERISTICS (CLASS "A")

Anode Voltage	300	500	volts
Anode Current	83	50	mA
Screen Voltage	250	200	volts
Screen Current	8.0	1.6	mA
Control Grid (g ₁) Voltage	-12.5	-14.5	volts
Cathode Bias Resistor	140	280	ohms
Anode Impedance	24,000	39,000	ohms
Mutual Conductance	6.5	5.7	mA/V
Optimum Load	3,000	6,000	ohms
Power Output	6.4	11.5	watts
Harmonic Distortion	6	12	per cent.

OPERATION AS PUSH-PULL AMPLIFIER (2 VALVES)

	Class AB1		Class AB2*	
Anode Voltage	500	600	600	volts
Anode Current (Zero Signal)	100	80	60	mA
Anode Current (Max. Signal)	119	150	200	mA
Screen Voltage	300	300	300	volts
Screen Current (Zero Signal)	2.5	1.5	1.5	mA
Screen Current (Max. Signal)	16.5	17.5	21	mA
Control Grid Voltage	-	-27.5	-30	volts
Cathode Bias Resistor	270	-	-	ohms
Peak Input (Grid to Grid)	72	59	78	volts
Optimum Load (Anode to Anode)	9,000	10,000	6,400	ohms
Power Output	32.5	47.5	80	watts
Harmonic Distortion	2.7	2.2	3.5	per cent.

* To obtain the maximum output at low distortion, the Anode and Screen supply voltages must not vary more than 5 per cent. nor the grid bias 3 per cent. between no signal and full signal conditions.

