

HF MULTI-BAND WIRE DIPOLE (TRAP DIPOLE) ANTENNAS

W-SERIES

W-8010 80m/40m/20m/15m/10m Five Band Trap Dipole Antenna

W-735 80m/40m Dual-Band Trap Dipole Antenna

W-721 40m/15m Dual-Band Trap Dipole Antenna



OPERATION INSTRUCTIONS

● **Parts List**

Each model contains the following parts in the package. Please confirm each part according to the list.

	W-8010	W-735
BU-50 BALUN with two screws, nuts and washers	1	1
80m trap	2	2
40m trap	2	-
20m trap	2	-
Wire element A 3.75m (12.3')	2	-
Wire element B 4.2m (13.8')	2	-
Wire element C 2.8m (9.2')	2	-
Wire element D 2.8m (9.2')	2	-
Wire element E 1.4m (4.6')	2	-
Wire element F 10.95m (35.9')	-	2
Wire element G 2.9m (9.5')	-	2
Wire element H 3.75m (12.3')	-	-
Wire element I 3.4m (11.2')	-	-
Adjustment element 0.4m (1.3')	6	6
Insulator	4	4
Nylon rope 10m(32.8')	2	2
Self-melting plastic sealing tape 0.3m (1.0')	1	1
Binding wire 0.6m (2.0')	2	2

● **Description**

1. The W-Series antennas are very easy to assemble. And, low stretch ratio, rugged and weather proof 3.5 square plastic coated stranded wire is employed for element material.
2. Adjustment element is provided for each band to adjust each band without affecting rest of the bands.
3. Completely molded wideband balun enables perfect weather proof performance.

● **Assembled antennas**

