

S-MRFGEN



Generator - RF Signal

Compact solid state RF signal generator designed for the hobbyist, service bench and technical instruction. The generator is most suited for checking and aligning the IF circuit and tuners in AM, FM, and TV's. 100KHz to 150MHz in 6 bands and up to 450MHz on third harmonics. 5.9" high x 9.8" wide x 5.1" deep.

Features:

- Wide frequency range- 100 Khz to 150 MHz
- With 1 KHz oscillator purpose of modulation
- High Stability
- Output control- 0dB/-20dB/-40dB and fine adjuster
- Frequency accuracy + or - 5%
- RF output- 100mV rms appx. (up to 35MHz unloaded)
- Output control- High-low switch, fine adjust
- Audio output 1 KHz min., 2V rms
- Modulation: Internal: 1 KHz (AM) 30% appx., External: 50 Hz ~ 20 KHz at < 1V rms input